



Daviscomms BR802 Pager

Bravo 802 Features

- * POCSAG / FLEX Coding Format
- * 4-Line Alpha Display with 20 Chars/Line
- * Zoom in from 4-Line to 2-Line Display
- * 7 POCSAG / 16 FLEX Addresses
- * Vibrate / Vibrate then Audible / No Alert / 8 Pleasing Alert Modes
- * Battery Level Indicator
- * Memory Retention
- * Out of Range Indicator
- * Time and Date Stamping

The **Daviscomms Br802** is a synthesized 4-Line alphanumeric pager that comes in both POCSAG and FLEX models. Important differences between the two pager models are the POCSAG version is available in the VHF, UHF, or 900 MHz frequency ranges while the FLEX version is available in the 900 MHz band only. Also, the POCSAG version has wideband and narrowband channel spacing while the FLEX model has only wideband capability.

Four lines of text can display 20 characters per line or up to 80 characters total and can also zoom to a larger two line view for easier reading. Messaging capabilities include Time and Date Stamping, 3-Speed Page Scrolling, Unread Message Reminder Alert, and Message Retention when off or changing the battery. The Br802 stores and protects messages in the following manner:

- Stores up to (30 - FLEX / 40 - POCSAG) Inbox Messages
- Stores up to (15 - FLEX / 24 - POCSAG) Information Service Messages
- Protects up to (15 - FLEX / 20 - POCSAG) Inbox Messages
- Protects up to (16 - FLEX / 20 - POCSAG) Saved Messages

Protecting messages prevents them from being replaced when memory is full.