









NEVER MISS THE IMPORTANT CALLS, ANYMORE

[FEATURES:]

EXTRA Loud Alert

Uni MAX will definitely get your attention. No more worries about missing important calls whether you are sleeping or far away from the pagers / cell phones or in a high noise environment.

Escalating Alert

Although the Uni MAX will provide a very loud alert tone it does it in escalating steps. Starting at low volume, it increments to the loudest setting after 30 seconds allowing the User plenty of time to reset it.

Works with Most Wireless Devices

Uni MAX will work with most pagers and cell phones.

Visual Indications

A large red LED flashes on Reset Button when a call is received that will easily catch the user's attention Also, a smaller flashing green LED indicates the Uni MAX is active and battery status.

Flexible Alert Time Settings

A 4-step slide switch provides for muting or setting the alert tone for 1 minute, 3 minutes, or continuous duration.

A friendly design to set mute mode, when you don't need an audible alert.

Selectable Alert Tone

Simply choose your favorite from a selection of ten (10) different tones. When alerting, the Uni MAX slowly increases the alert volume allowing the User to reset it before it reaches maximum volume.

Rotate Protection on Volume Control Knob

The volume knob has distinct indent settings that will keep the volume control from mistakenly being changed.

Variety of Power Sources

Uni MAX is not only powered by an accessorized AC adapter, you can also choose AA Alkaline batteries or the rechargeable battery pack (optional). This ensures operation in case of AC power black outs or if one wants to use the Uni MAX outdoors.

Very Low Power Consumption

The Uni MAX will operate for more than 20 days on AA batteries in the absence of AC power.

Durability

The Uni MAX is built to Unication's exacting long term reliability testing standards. As with all Unication products, the Uni MAX has to pass our accelerated life testing that simulates 10 years of in field use. This is Unication's commitment to quality and customer satisfaction.


(SPECIFICATIONS:)

Alert Tone SPL	Max. >100 dB @ 30 cm, Min. >70 dB @ 30 cm (Volume control on minimum)
Battery Status Indication	Battery Full -> LED ON (Green)
Battery Charging	LED ON (Orange)
Battery Half Capacity	LED Flash (Orange)
Battery Low	LED Flash (Red)
Operating Temperature	0° C ~ +50° C
Operating Humidity	< 85%
Storage Temperature	-20° C ~ +85° C
Powered by Standard Battery	AA Alkaline Battery x 3
Powered by Rechargeable Battery	Battery Pack (Ni-MH 62U x 3)
Dimension	9.6W x 7.8H x 5.1D cm
Weight	120 gram (Not include battery)
AC Plug type	US / EURO / AUS / UK

Uni MAX is perfect for following Unication Products: Alpha Elite / Alpha Gold / Alpha Elegant / Alpha Legend / NP-88 / NP-30 / NP-20 / TP-21 / M90



ACCESSORIES :











NP - 88 Series

AC Power Adapter (Standard)

Battery Pack (Optional)



Corporate Headquarter:

Unication Co., Ltd.
Tel.: +886-2-22999678
Address: 5F., No.6, Wu-Kung 5Rd.,
Hsinchunag City, Taipei, Taiwan.
E-mail:salesenquiry@uni.com.tw

Dallas Office:

Unication USA Inc.
Tel.: +1-817-303-9320
Address: 1901 E. Lamar Blvd.,
Arlington, TX 76006, U.S.A.
Email:sales@unication.com

www.unication.com www.uni.com.tw